

Stand-alone Detectors

NB-138 Water Detector

12V + NO/NC output for Security Panel connection is available

Protect your home from potential water flood damage by placing anywhere a potential water leak exists -- near or beneath sump pumps, plumbing, refrigerators, dishwashers, washing machines, sinks, water heaters, toilets, basements and garages

Product Features

- Sounding a loud alarm signal of exceeding 85 dB at 10 feet at alarm mode
- Using advanced electronic design to accurately detect the water leakage.
- Alarm signal is able to last for up to 72 hours.
- Easy installation and maintenance.
- Fully automatic operation.
- Ergonomic design of detector casing

Product Specification

Dimensions :	100mm x 62mm x 35mm
Weight :	2.4 oz. (68 g) without battery
Battery Type :	9 Volt alkaline (not included)
Battery Life :	5 years
Sound Intensity :	85dB @ 10 feet (3.0 m)
Operating Temperature :	32°F to 120°F (0°C to 49°C)
Storage Temperature :	-20°F to 150°F (-29°C to 66°C)
Humidity :	80%RH (non-condensing)
Shock Resistance :	Shock resistant from a 6-ft. (1.8 m) drop onto concrete
Water Resistance :	Splash and water resistant, but not waterproof. Floats on surface.

